

Mercusys MR80X AX3000 Dual Band Gigabit WiFi 6 Router

Sale Price: 3990.0



PRODUCT ID: 0011668

Data Rate	2402 Mbps (5 GHz) + 574 Mbps (2.4 GHz)
Antenna	4x 5 dBi Fixed Omni-Directional Antennas
Button	Reset/WPS Button
Frequency	2.4 GHz < 20dBm (EIRP) 5 GHz < 23dBm (band1、 band2) 5 GHz < 30dBm (band3)
Wireless	Enable/Disable Wireless Radio, WMM
Interface	1x Gigabit WAN Port + 3x Gigabit LAN Ports
Network Standard	Compatible with 802.11ax/ac/a/b/g/n Wi-Fi standards
Encryption	WEP, WPA / WPA2-Personal, WPA2 / WPA3-Personal
Ports	Network Services Enabled by Default Web Server Manage and configure device through web (HTTP/HTTPS) Port: 80/443; Protocol: TCP DHCP Server IP address assignment (DHCP) Port: 67; Protocol: UDP DNS Port: 53; Protocol: TCP & UDP App management Manage and configure device through app Port: 20001; Protocol: TCP Port: 20002; Protocol: UDP

11g 54Mbps: -79dBm
11n HT40 MCS7:-74dBm
11n HT20 MCS7:-77dBm
11a 6Mbps: -97dBm
11a 54Mbps: -79dBm
11ac VHT20 MCS8:-75dBm
11ac VHT40 MCS9:-71dBm
11ac VHT80 MCS9:-67dBm
11ax VHT20 MCS11:-67dBm
11ax VHT40 MCS11:-64dBm
11ax VHT80 MCS11:-61dBm

Operating System Support

WAN Type

Dynamic IP/Static IP/PPPoE/L2TP/PPTP

Management

Access Control

Local Management

Remote Management

NAT Forwarding

Port Forwarding, Port Triggering, UPnP, DMZ

Firewall Security

SPI Firewall, IP and MAC Address Binding

Guest Network

2.4 GHz Guest Network, 5 GHz Guest Network

DHCP

Server, DHCP Client List

VPN Server

OpenVPN, PPTP supported